

5.1 MOTOR STEPPING PROM 82S23N-1

ADDRESS (DECIMAL)	Y1	Y2	Y3	Y4	Y5	Y6	Y7	Y8
0	X		X			X	X	
1		X	X	X				
2	X	X		X	X			
3					X	X		
4	X	X	X			X	X	
5			X	X				
6	X			X	X			
7		X			X	X		
8	X		X			X		
9		X	X	X				
10	X	X		X	X			
11					X	X		
12	X	X	X			X		
13			X	X				
14	X			X	X			
15		X			X	X		
16			X			X	X	
17	X		X	X				
18		X		X	X			
19	X	X			X	X		
20			X			X	X	
21	X		X	X				
22		X		X	X			
23	X	X			X	X		
24			X			X		
25	X		X	X				
26		X		X	X			
27	X	X			X	X		
28			X			X		
29	X		X	X				
30		X		X	X			
31	X	X			X	X		

X = HIGH LEVEL

5.2 CONTROL SIGNAL DECODING PROM 82S23N-II (X3110 ONLY)

ADDRESS (DECIMAL)	US-N Y1	WE Y2	WEX Y3	USD Y4	WPX-N Y5	WPXX Y6	HL-N Y7	HLR-N Y8
0	X				X		X	X
1	X				X		X	X
2	X				X		X	X
3	X				X		X	X
4	X					X	X	X
5	X					X	X	X
6	X					X	X	X
7	X					X	X	X
8	X				X		X	
9	X				X		X	
10	X				X		X	
11	X				X		X	
12	X					X	X	
13	X					X	X	
14	X					X	X	
15	X					X	X	
16				X	X		X	X
17				X	X		X	X
18				X	X		X	X
19				X	X		X	X
20				X		X	X	X
21				X		X	X	X
22				X		X	X	X
23				X		X	X	X
24	X	X	X	X	X			
25				X	X			
26	X	X	X	X	X		X	
27				X	X		X	
28				X		X		
29				X		X		
30				X		X	X	
31				X		X	X	

X = HIGH LEVEL